

Plastic Impeller Fan series

塑料葉輪系列



- With small compact structure and flange frame, it is convenient for installation.
- Shaded pole asynchronous 2 poles motor design, full dynamic and free maintenance.
- Various kinds of models can satisfy the requirement of many industrial fields.
- Sleeve bearing can realize very low noise.
- Ball bearing can endure bad running environment.
- Different specifications can provide different voltages and air volume.
- Wide choice for fan accessories: different sizes of metal finger guards, plastic finger guards, filter pad, air filter, lead wires and so on.
- The fans have approvals of TUV, CSA, CE, CCC and RoHS.

- 結構緊湊而小巧,法蘭式框安裝方便
- 罩極異步兩極電機設計,動力實足,免維護
- 品種多樣,能滿足眾多的工業領域的要求
- 含油軸承能夠實現很低的噪音
- 滾珠軸承設計能夠使用在極惡劣的工作環境
- 多種規格可以滿足各種電壓和風量
- 提供很多的風機配件,不同型號的金屬網罩,塑料網罩,過濾網,過濾器,連接電線及其他零件
- 獲得TUV,CSA,CE,CCC和RoHS認證

Common Models description

常規型號說明



F | J

fan serial number
風扇編號

1 | 2 | 0 | 3

The fan frame size
風扇外框尺寸

Frame Size(mm)	Frame Thickness(cm)
80.=80	2.=2.5
90.=92	3.=3.8
120.=119	5.=5.1
150.=150	6.=6.0(6.5)
172.=Ø172	
180.=180	
230.=Ø230	

2

Input Voltage
輸入電壓

- 1. 115V
- 2. 230V
- 3. 380V

A | B

Other functions
特殊功能

- T.The plug-in connection
- L. lead wire connection
- V.Suck
- A.Blow

T

Suffix: Type of configuration

- 后綴:類型的配置
- A.aluminum alloy frame
 - P.Plastic frame
 - B.ball bearing
 - S.Sleeve bearing



References are based on the frame dimension, which helps you to quickly select the best choice for your installation.

引用基于外殼尺寸,這能讓你快速選擇你安裝的最佳選擇

Example:

> When your installation space is enough for dimension 120*120*38mm, please choose FJ1203

當你安裝空間足夠尺寸 120X120X38mm,請選擇 FJ1203



> When you choose AC 220V, frame size 120x120x38mm, sleeve bearing, plug-in connection, please choose model FJ12032AST

當你選擇電壓 220V 外框尺寸 120X120X38mm,馬達轉動部份是選含油軸承時,引出線連接採用插件方式時,
請選擇 FJ12032AST

> We can customize your unconventional products.

我們可非常規量身定製您的產品